## **ECONOLINE - DC/DC-Converter**

RX and RY Series, 1 Watt, DIP14/SIP7, Regulated (Single Output)



#### **Features**

- Load Voltage Regulation <1.5%
- Controllable Output
- 1kVDC Isolation
- SIP & DIP Package Styles
- UL 94V-0 Package Material
- No Heatsink Required
- Toroidal Magnetics
- Fully Encapsulated






#### **Selection Guide**

Part Number	Part Number	Input Voltage	Output Voltage	Output Current	Efficiency
DIP14	SIP7	(VDC)	(VDC)	(mA)	(%)
RX-XX05S	RY-XX05S	5, 9, 12, 15, 24	5	180	58-60
RX-XX09S	RY-XX09S	5, 9, 12, 15, 24	9	111	56-62
RX-XX12S	RY-XX12S	5, 9, 12, 15, 24	12	84	60-66
RX-XX15S	RY-XX15S	5, 9, 12, 15, 24	15	66	60-66
RX-XX24S	RY-XX24S	5, 9, 12, 15, 24	24	42	60-68


## Specifications (Core Operating Area) and Operating Temperature / Derating-Graph

openious (core openius 7 sea, and openius femperature 7 serating to					
Input Voltage					
Input Filter					
Output Voltage Accuracy					
Line Voltage Regulation					
Load Voltage Regulation (10% to 100% full load)					
Ripple and Noise Output					
Efficiency at Full Load					
Isolation Voltage					
Isolation Resistance (Viso = 500VDC)					
Isolation Capacitance					
Short Circuit Protection					
Switching Frequency at Full Load					
Operating Temperature					
	-55°C to +125°C				
RX types RY types	2.9g 2.8g				
	RX types				




## **Typical Applications**

## Flash PROM Programming Voltage Control



## Normal Isolated Regulated Output




# ECONOLINE - DC/DC-Converter

RX and RY Series, 1 Watt, DIP14/SIP7, Regulated (Single Output)



## Package Style and Pinning (mm)

### 8 PIN DIP Package








3.05


7.62


### 7 PIN SIP Package













### **Recommended Footprint Details**

12.70





### Pin Connections

Pin #	RX	RY
1	–Vin	+Vin
2	No Pin	–Vin
4	No Pin	–Vout
5	No Pin	CTRL
6	No Pin	+Vout
9	+Vout	No Pin
10	CTRL	No Pin
11	–Vout	No Pin
14	+Vin	No Pin

XX.X  $\pm$  0.5 mm XX.XX  $\pm$  0.25 mm